

Serial No. 10/700,310

Docket No. NG(ST)6564

RECEIVED  
CENTRAL FAX CENTER

JUN 06 2007

LISTING OF THE CLAIMS

This listing of claims will replace all prior versions, and listings, of claims in the application:

1. (Currently Amended) A multi-carrier transmitter assembly, comprising:
  - a digital exciter that provides a digital multi-carrier signal from baseband data;
  - a digital-to-analog converter that converts the digital multi-carrier signal into an analog multi-carrier signal;
  - a signal distributor that ~~distributes~~ deserializes the analog multi-carrier signal into a plurality of analog carrier signals; and
  - a plurality of antennas, each of the plurality of antennas transmitting at least one of the plurality of analog carrier signals.
2. (Original) The assembly of claim 1, the signal distributor comprising at least one filter, the at least one filter being electrically adjustable by the exciter as to change at least one frequency characteristic associated with the at least one filter.
3. (Original) The assembly of claim 2, the at least one filter comprising a surface acoustic wave (SAW) filter having at least one electrically actuatable micromechanical structures.
4. (Original) The assembly of claim 2, the at least one frequency characteristic comprising a center frequency of a passband associated with the at least one filter.
5. (Original) The assembly of claim 2, the at least one frequency characteristic comprising respective center frequencies of a plurality of passbands, the center frequency of each passband being electrically adjustable by the exciter.

Serial No. 10/700,310

Docket No. NG(ST)6564

6. (Original) The assembly of claim 2, the at least one frequency characteristic being a center frequency of a stopband associated with the at least one filter.
7. (Original) The assembly of claim 2, the at least one frequency characteristic comprising respective center frequencies of a plurality of stopbands, the center frequency of each stopband being electrically adjustable by the exciter.
8. (Original) The assembly of claim 1, the signal distributor comprising a time division demultiplexer.
9. (Original) The assembly of claim 1, the signal distributor comprising a plurality of decoders, providing respective despreading codes to a multi-carrier signal.
10. (Original) The assembly of claim 1, the exciter and the digital-to-analog converter being located at a first location, and at least one of the plurality of antennas being located at a second location, spatially remote from the first location.
11. (Original) The assembly of claim 10, at least one antenna being located at a third location, spatially remote from the first location and the second location.
12. (Currently Amended) A multi-carrier receiver assembly, comprising:  
at least one antenna, a plurality of analog carrier signals being received at the at least one antenna;  
at least one passband filter, each of the at least one passband filter being associated with a respective one of the at least one antenna, having a plurality of passbands, a respective center frequency of each passband being electrically adjustable by the digital processing assembly;

Serial No. 10/700,310

Docket No. NG(ST)6564

a signal combiner that combines the analog carrier signals at least one antenna into an analog multi-carrier signal;

an analog-to-digital converter that converts the analog multi-carrier signal into a digital multi-carrier signal; and

a digital processing assembly that processes the digital multi-carrier signal to extract information from the multi-carrier signal.

13. (Original) The receiver assembly of claim 12, the signal combiner comprising at least one mixer for downconverting analog carrier signals, a given mixer being associated with a respective one of the at least one antennas and having an associated intermediate frequency.

14. (Original) The receiver assembly of claim 12, the signal combiner comprising a frequency multiplexer.

15. (Original) The receiver assembly of claim 12, the signal combiner comprising a code division multiple access multiplexer.

16. (Original) The receiver assembly of claim 12, the signal combiner comprising a plurality of coders that provide respective spreading codes to the analog carrier signals, the respective spreading codes being mutually orthogonal.

17. (Original) The receiver assembly of claim 12, the at least one antenna having respective associated tracking assemblies that determine a frequency band associated with an interfering signal.

18. (Original) The receiver assembly of claim 17, the at least one antenna having respective associated stopband filters that attenuate the interfering signal in response to the determination of the associated tracking assembly.

Serial No. 10/700,310

Docket No. NG(ST)6564

19. (Cancelled)

20. (Original) The receiver assembly of claim 12, the at least one antenna having respective cancellation assemblies that generate an inverted phase representation of at least one interfering signal received at their respective antennas.

21. (Original) The receiver assembly of claim 12, the at least one antenna being one antenna and the signal combiner comprising a bypass, such that a carrier signal from the antenna can bypass the signal combiner.

22. (Original) The receiver assembly of claim 21, the at least one antenna having respective associated tracking assemblies that determine a frequency band associated with an interfering signal.

23. (Original) The receiver assembly of claim 22, the at least one antenna having respective associated stopband filters that attenuate the interfering signal in response to the determination of the associated tracking assembly.

24. (Original) The receiver assembly of claim 21, the at least one antenna having respective passband filters, the filters having a plurality of passbands, a respective center frequency of each passband being electrically adjustable by the digital processing assembly.

25. (Original) The receiver assembly of claim 21, the at least one antenna having respective cancellation assemblies that generate an inverted phase representation of at least one interfering signal received at their respective antennas.

Serial No. 10/700,310

Docket No. NG(ST)6564

26. (Original) The receiver assembly of claim 12, the analog-to-digital converter and the digital processing assembly being located at a first location, and a first of the at least one antenna being located at a second location, spatially remote from the first location.

27. (Original) The receiver assembly of claim 26, a second of the at least one antenna being located at a third location, spatially remote from the first location and the second location.

28. (Currently Amended): A multi-carrier transceiver system, comprising:

means for combining a plurality of carrier signals into a combined multi-carrier signal represented in a first domain;

means for converting the combined multi-carrier signal from the first domain to a second domain;

means for determining a frequency band associated with an interfering signal; and

means for distributing the converted multi-carrier signal into a plurality of signals represented in the second domain.

29. (Original) The system of claim 28, the means for converting the multi-carrier signal from a first domain to a second domain comprising means for converting a digital multi-carrier signal into an analog multi-carrier signal.

30. (Original) The system of claim 28, the means for converting the multi-carrier signal from a first domain to a second domain comprising means for converting an analog multi-carrier signal into a digital multi-carrier signal.

31. (Cancelled)

32. (Currently Amended): The system of claim ~~[[31]]~~ 28, means for attenuating the interfering signal in response to the determination of the associated tracking assembly.

Serial No. 10/700,310

Docket No. NG(ST)6564

33. (Original) The system of claim 28, further comprising means for generating an inverted phase representation of at least one interfering signal associated with the plurality of carrier signals.

34. (Currently Amended): A method of transmitting a multi-carrier signal, comprising:  
generating a digital multi-carrier signal at an exciter;  
converting the digital multi-carrier signal into an analog multi-carrier signal;  
distributing the analog multi-carrier signal into a plurality of analog signals, where distributing the analog multi-carrier signal comprises filtering a plurality of copies of the multi-carrier analog signal at respective tunable filters, at least one of the tunable filters being a multiband tunable filter; and  
providing the plurality of analog signals to respective antennas for transmission.

35 and 36. (Cancelled)

37. (Original) The method of claim 34, the distributing of the analog multi-carrier signal comprising deserializing a plurality of carrier signals comprising the multi-carrier signal.

38. (Currently Amended): A method of processing a plurality of carrier signals, comprising:  
receiving a plurality of analog carrier signals at a plurality of antennas;  
generating an inverted phase representation of at least one interfering signal associated with the plurality of carrier signals;  
combining the plurality of analog carrier signals into a multi-carrier analog signal;  
converting the analog multi-carrier signal into a digital multi-carrier signal; and  
processing the digital multi-carrier signal at a digital processing assembly.

Serial No. 10/700,310

Docket No. NG(ST)6564

39. (Original) The method of claim 38, the combining of the plurality of analog carrier signals comprising converting each received carrier signal to a unique frequency.

40. (Original) The method of claim 38, the combining of the plurality of analog carrier signals comprising applying a spreading code to each of the analog carrier signals and summing.

41. (Original) The method of claim 38, further comprising determining a frequency band associated with an interfering signal.

42. (Original) The method of claim 41, further comprising attenuating the interfering signal in response to the determination of the associated tracking assembly.

43. (Cancelled).

44. (Currently Amended): A receiver assembly, comprising:

at least one antenna a plurality of antennas that each receive receives an analog signal comprising at least one frequency band of interest and at least one frequency band containing an interfering signal;

an analog-to-digital converter that creates a digital representation of the each analog signal;

a digital processing component that receives the digital representation of the each analog signal and produces a control signal from each digital representation, representing an associated antenna, specifying the at least one frequency band containing the interfering signal; and

at least one a plurality of adjustable filter filters, each adjustable filter being associated with one of the plurality of antennas, a given adjustable filter being electrically adjustable to change at least one frequency characteristic associated with the filter in response to the control signal associated with the associated antenna of the given adjustable filter[.]] that attenuates as

Serial No. 10/700,310

Docket No. NG(ST)6564

to attenuate the specified at least one frequency band within the analog signal received at the associated antenna of the given adjustable filter.

45. (Original) The assembly of claim 44, the attenuation component comprising a stop band filter, being electrically adjustable in response to the control signal as to change a center frequency associated with at least one stopband.
46. (Original) The assembly of claim 44, the attenuation component comprising a pass band filter, being electrically adjustable in response to the control signal as to change a center frequency associated with at least one passband.
47. (Cancelled).
48. (Currently Amended) The assembly of claim [[47]] 44, comprising a signal combiner that combines the analog signals from the plurality of antennas into a multi-carrier signal and an analog-to-digital converter that converts the analog multi-carrier signal into a digital multi-carrier signal.